

OV SERIES - LED

PHOTOMETRIC DATA GUIDE - LUMEN TABLES (OV1-LED)

Filename	[LUMCAT]	Watts	Lum Lumens	LER	BUG
OV1-CA-LED-GRV-III-24LED-350mA-27K.ies	OV1-CA-LED-GRV-III-24LED-350mA-27K	26	2131	82	B1-U4-G2
OV1-CA-LED-GRV-III-36LED-350mA-27K.ies	OV1-CA-LED-GRV-III-36LED-350mA-27K	40	3200	80	B1-U5-G2
OV1-CA-LED-GRV-V-24LED-350mA-27K.ies	OV1-CA-LED-GRV-V-24LED-350mA-27K	26	2083	80	B1-U4-G2
OV1-CA-LED-GRV-V-36LED-350mA-27K.ies	OV1-CA-LED-GRV-V-36LED-350mA-27K	40	3127	78	B1-U5-G2
OV1-CA-LED-GRV-III-24LED-350mA-30K.ies	OV1-CA-LED-GRV-III-24LED-350mA-30K	26	2301	88	B1-U4-G2
OV1-CA-LED-GRV-III-36LED-350mA-30K.ies	OV1-CA-LED-GRV-III-36LED-350mA-30K	40	3455	86	B1-U5-G3
OV1-CA-LED-GRV-V-24LED-350mA-30K.ies	OV1-CA-LED-GRV-V-24LED-350mA-30K	26	2247	86	B1-U4-G2
OV1-CA-LED-GRV-V-36LED-350mA-30K.ies	OV1-CA-LED-GRV-V-36LED-350mA-30K	40	3376	84	B1-U5-G3
OV1-CA-LED-GRV-III-24LED-350mA-40K.ies	OV1-CA-LED-GRV-III-24LED-350mA-40K	26	2422	93	B1-U4-G2
OV1-CA-LED-GRV-III-36LED-350mA-40K.ies	OV1-CA-LED-GRV-III-36LED-350mA-40K	40	3637	91	B1-U5-G3
OV1-CA-LED-GRV-V-24LED-350mA-40K.ies	OV1-CA-LED-GRV-V-24LED-350mA-40K	26	2366	91	B1-U4-G2
OV1-CA-LED-GRV-V-36LED-350mA-40K.ies	OV1-CA-LED-GRV-V-36LED-350mA-40K	40	3553	89	B1-U5-G3
OV1-CA-LED-GRV-III-24LED-350mA-50K.ies	OV1-CA-LED-GRV-III-24LED-350mA-50K	26	2543	98	B1-U4-G2
OV1-CA-LED-GRV-III-36LED-350mA-50K.ies	OV1-CA-LED-GRV-III-36LED-350mA-50K	40	3818	95	B1-U5-G3
OV1-CA-LED-GRV-V-24LED-350mA-50K.ies	OV1-CA-LED-GRV-V-24LED-350mA-50K	26	2484	96	B1-U4-G2
OV1-CA-LED-GRV-V-36LED-350mA-50K.ies	OV1-CA-LED-GRV-V-36LED-350mA-50K	40	3729	93	B1-U5-G3
OV1-WA-LED-VPA-ASY-48LED-350mA-27K.ies	OV1-WA-LED-VPA-ASY-48LED-350mA-27K	53	4970	94	B1-U5-G3
OV1-WA-LED-VPA-ASY-48LED-525mA-27K.ies	OV1-WA-LED-VPA-ASY-48LED-525mA-27K	76	7057	93	B2-U5-G4
OV1-WA-LED-VPA-ASY-64LED-350mA-27K.ies	OV1-WA-LED-VPA-ASY-64LED-350mA-27K	70.4	6626	94	B1-U5-G4
OV1-WA-LED-VPA-ASY-64LED-525mA-27K.ies	OV1-WA-LED-VPA-ASY-64LED-525mA-27K	102	9409	92	B2-U5-G4
OV1-WA-LED-VPA-ASY-80LED-350mA-27K.ies	OV1-WA-LED-VPA-ASY-80LED-350mA-27K	86	8282	96	B2-U5-G4
OV1-WA-LED-VPA-SYM-48LED-350mA-27K.ies	OV1-WA-LED-VPA-SYM-48LED-350mA-27K	53	5097	96	B2-U5-G3
OV1-WA-LED-VPA-SYM-48LED-525mA-27K.ies	OV1-WA-LED-VPA-SYM-48LED-525mA-27K	76	7238	95	B2-U5-G3
OV1-WA-LED-VPA-SYM-64LED-350mA-27K.ies	OV1-WA-LED-VPA-SYM-64LED-350mA-27K	70.4	6797	97	B2-U5-G3
OV1-WA-LED-VPA-SYM-64LED-525mA-27K.ies	OV1-WA-LED-VPA-SYM-64LED-525mA-27K	102	9651	95	B3-U5-G4
OV1-WA-LED-VPA-SYM-80LED-350mA-27K.ies	OV1-WA-LED-VPA-SYM-80LED-350mA-27K	86	8496	99	B2-U5-G4
OV1-WA-LED-VPA-ASY-48LED-350mA-30K.ies	OV1-WA-LED-VPA-ASY-48LED-350mA-30K	53	5365	101	B1-U5-G3
OV1-WA-LED-VPA-ASY-48LED-525mA-30K.ies	OV1-WA-LED-VPA-ASY-48LED-525mA-30K	76	7618	100	B2-U5-G4
OV1-WA-LED-VPA-ASY-64LED-350mA-30K.ies	OV1-WA-LED-VPA-ASY-64LED-350mA-30K	70.4	7153	102	B2-U5-G4
OV1-WA-LED-VPA-ASY-64LED-525mA-30K.ies	OV1-WA-LED-VPA-ASY-64LED-525mA-30K	102	10158	100	B2-U5-G5
OV1-WA-LED-VPA-ASY-80LED-350mA-30K.ies	OV1-WA-LED-VPA-ASY-80LED-350mA-30K	86	8941	104	B2-U5-G4
OV1-WA-LED-VPA-SYM-48LED-350mA-30K.ies	OV1-WA-LED-VPA-SYM-48LED-350mA-30K	53	5502	104	B2-U5-G3
OV1-WA-LED-VPA-SYM-48LED-525mA-30K.ies	OV1-WA-LED-VPA-SYM-48LED-525mA-30K	76	7814	103	B2-U5-G3
OV1-WA-LED-VPA-SYM-64LED-350mA-30K.ies	OV1-WA-LED-VPA-SYM-64LED-350mA-30K	70.4	7337	104	B2-U5-G3
OV1-WA-LED-VPA-SYM-64LED-525mA-30K.ies	OV1-WA-LED-VPA-SYM-64LED-525mA-30K	102	10418	102	B3-U5-G4
OV1-WA-LED-VPA-SYM-80LED-350mA-30K.ies	OV1-WA-LED-VPA-SYM-80LED-350mA-30K	86	9172	107	B2-U5-G4
OV1-WA-LED-VPA-ASY-48LED-350mA-40K.ies	OV1-WA-LED-VPA-ASY-48LED-350mA-40K	53	5647	107	B1-U5-G3
OV1-WA-LED-VPA-ASY-48LED-525mA-40K.ies	OV1-WA-LED-VPA-ASY-48LED-525mA-40K	76	8019	106	B2-U5-G4
OV1-WA-LED-VPA-ASY-64LED-350mA-40K.ies	OV1-WA-LED-VPA-ASY-64LED-350mA-40K	70.4	7529	107	B2-U5-G4
OV1-WA-LED-VPA-ASY-64LED-525mA-40K.ies	OV1-WA-LED-VPA-ASY-64LED-525mA-40K	102	10692	105	B2-U5-G5
OV1-WA-LED-VPA-ASY-80LED-350mA-40K.ies	OV1-WA-LED-VPA-ASY-80LED-350mA-40K	86	9412	109	B2-U5-G4
OV1-WA-LED-VPA-SYM-48LED-350mA-40K.ies	OV1-WA-LED-VPA-SYM-48LED-350mA-40K	53	5792	109	B2-U5-G3
OV1-WA-LED-VPA-SYM-48LED-525mA-40K.ies	OV1-WA-LED-VPA-SYM-48LED-525mA-40K	76	8225	108	B2-U5-G3
OV1-WA-LED-VPA-SYM-64LED-350mA-40K.ies	OV1-WA-LED-VPA-SYM-64LED-350mA-40K	70.4	7724	110	B2-U5-G3
OV1-WA-LED-VPA-SYM-64LED-525mA-40K.ies	OV1-WA-LED-VPA-SYM-64LED-525mA-40K	102	10967	108	B3-U5-G4
OV1-WA-LED-VPA-SYM-80LED-350mA-40K.ies	OV1-WA-LED-VPA-SYM-80LED-350mA-40K	86	9654	112	B3-U5-G4
OV1-WA-LED-VPA-ASY-48LED-350mA-50K.ies	OV1-WA-LED-VPA-ASY-48LED-350mA-50K	53	5929	112	B1-U5-G3
OV1-WA-LED-VPA-ASY-48LED-525mA-50K.ies	OV1-WA-LED-VPA-ASY-48LED-525mA-50K	76	8420	111	B2-U5-G4
OV1-WA-LED-VPA-ASY-64LED-350mA-50K.ies	OV1-WA-LED-VPA-ASY-64LED-350mA-50K	70.4	7906	112	B2-U5-G4
OV1-WA-LED-VPA-ASY-64LED-525mA-50K.ies	OV1-WA-LED-VPA-ASY-64LED-525mA-50K	102	11227	110	B2-U5-G5
OV1-WA-LED-VPA-ASY-80LED-350mA-50K.ies	OV1-WA-LED-VPA-ASY-80LED-350mA-50K	86	9883	115	B2-U5-G5
OV1-WA-LED-VPA-SYM-48LED-350mA-50K.ies	OV1-WA-LED-VPA-SYM-48LED-350mA-50K	53	6082	115	B2-U5-G3
OV1-WA-LED-VPA-SYM-48LED-525mA-50K.ies	OV1-WA-LED-VPA-SYM-48LED-525mA-50K	76	8636	114	B2-U5-G4
OV1-WA-LED-VPA-SYM-64LED-350mA-50K.ies	OV1-WA-LED-VPA-SYM-64LED-350mA-50K	70.4	8110	115	B2-U5-G3
OV1-WA-LED-VPA-SYM-64LED-525mA-50K.ies	OV1-WA-LED-VPA-SYM-64LED-525mA-50K	102	11515	113	B3-U5-G4
OV1-WA-LED-VPA-SYM-80LED-350mA-50K.ies	OV1-WA-LED-VPA-SYM-80LED-350mA-50K	86	10137	118	B3-U5-G4

IES File downloads for this product can be found at www.usaltg.com/downloads/asr.html

OV SERIES - LED

PHOTOMETRIC DATA GUIDE - LUMEN TABLES (OV2-LED)

Filename	[LUMCAT]	Watts	Lum Lumens	LER	BUG
OV2-CA-LED-GRV-III-24LED-350mA-27K.ies	OV2-CA-LED-GRV-III-24LED-350mA-27K	26	2131	82	B1-U4-G2
OV2-CA-LED-GRV-III-36LED-350mA-27K.ies	OV2-CA-LED-GRV-III-36LED-350mA-27K	40	3200	80	B1-U5-G2
OV2-CA-LED-GRV-V-24LED-350mA-27K.ies	OV2-CA-LED-GRV-V-24LED-350mA-27K	26	2083	80	B1-U4-G2
OV2-CA-LED-GRV-V-36LED-350mA-27K.ies	OV2-CA-LED-GRV-V-36LED-350mA-27K	40	3127	78	B1-U5-G2
OV2-CA-LED-GRV-III-24LED-350mA-30K.ies	OV2-CA-LED-GRV-III-24LED-350mA-30K	26	2301	88	B1-U4-G2
OV2-CA-LED-GRV-III-36LED-350mA-30K.ies	OV2-CA-LED-GRV-III-36LED-350mA-30K	40	3455	86	B1-U5-G3
OV2-CA-LED-GRV-V-24LED-350mA-30K.ies	OV2-CA-LED-GRV-V-24LED-350mA-30K	26	2247	86	B1-U4-G2
OV2-CA-LED-GRV-V-36LED-350mA-30K.ies	OV2-CA-LED-GRV-V-36LED-350mA-30K	40	3376	84	B1-U5-G3
OV2-CA-LED-GRV-III-24LED-350mA-40K.ies	OV2-CA-LED-GRV-III-24LED-350mA-40K	26	2422	93	B1-U4-G2
OV2-CA-LED-GRV-III-36LED-350mA-40K.ies	OV2-CA-LED-GRV-III-36LED-350mA-40K	40	3637	91	B1-U5-G3
OV2-CA-LED-GRV-V-24LED-350mA-40K.ies	OV2-CA-LED-GRV-V-24LED-350mA-40K	26	2366	91	B1-U4-G2
OV2-CA-LED-GRV-V-36LED-350mA-40K.ies	OV2-CA-LED-GRV-V-36LED-350mA-40K	40	3553	89	B1-U5-G3
OV2-CA-LED-GRV-III-24LED-350mA-50K.ies	OV2-CA-LED-GRV-III-24LED-350mA-50K	26	2543	98	B1-U4-G2
OV2-CA-LED-GRV-III-36LED-350mA-50K.ies	OV2-CA-LED-GRV-III-36LED-350mA-50K	40	3818	95	B1-U5-G3
OV2-CA-LED-GRV-V-24LED-350mA-50K.ies	OV2-CA-LED-GRV-V-24LED-350mA-50K	26	2484	96	B1-U4-G2
OV2-CA-LED-GRV-V-36LED-350mA-50K.ies	OV2-CA-LED-GRV-V-36LED-350mA-50K	40	3729	93	B1-U5-G3
OV2-WA-LED-VPA-ASY-36LED-350mA-27K.ies	OV2-WA-LED-VPA-ASY-36LED-350mA-27K	40	3728	93	B1-U5-G3
OV2-WA-LED-VPA-ASY-36LED-525mA-27K.ies	OV2-WA-LED-VPA-ASY-36LED-525mA-27K	58	5293	91	B1-U5-G3
OV2-WA-LED-VPA-ASY-48LED-350mA-27K.ies	OV2-WA-LED-VPA-ASY-48LED-350mA-27K	53	4970	94	B1-U5-G3
OV2-WA-LED-VPA-SYM-36LED-350mA-27K.ies	OV2-WA-LED-VPA-SYM-36LED-350mA-27K	40	3823	96	B1-U5-G3
OV2-WA-LED-VPA-SYM-36LED-525mA-27K.ies	OV2-WA-LED-VPA-SYM-36LED-525mA-27K	58	5429	94	B2-U5-G3
OV2-WA-LED-VPA-SYM-48LED-350mA-27K.ies	OV2-WA-LED-VPA-SYM-48LED-350mA-27K	53	5097	96	B2-U5-G3
OV2-WA-LED-VPA-ASY-36LED-350mA-30K.ies	OV2-WA-LED-VPA-ASY-36LED-350mA-30K	40	4024	101	B1-U5-G3
OV2-WA-LED-VPA-ASY-36LED-525mA-30K.ies	OV2-WA-LED-VPA-ASY-36LED-525mA-30K	58	5713	99	B1-U5-G3
OV2-WA-LED-VPA-ASY-48LED-350mA-30K.ies	OV2-WA-LED-VPA-ASY-48LED-350mA-30K	53	5365	101	B1-U5-G3
OV2-WA-LED-VPA-SYM-36LED-350mA-30K.ies	OV2-WA-LED-VPA-SYM-36LED-350mA-30K	40	4127	103	B1-U5-G3
OV2-WA-LED-VPA-SYM-36LED-525mA-30K.ies	OV2-WA-LED-VPA-SYM-36LED-525mA-30K	58	5860	101	B2-U5-G3
OV2-WA-LED-VPA-SYM-48LED-350mA-30K.ies	OV2-WA-LED-VPA-SYM-48LED-350mA-30K	53	5502	104	B2-U5-G3
OV2-WA-LED-VPA-ASY-36LED-350mA-40K.ies	OV2-WA-LED-VPA-ASY-36LED-350mA-40K	40	4236	106	B1-U5-G3
OV2-WA-LED-VPA-ASY-36LED-525mA-40K.ies	OV2-WA-LED-VPA-ASY-36LED-525mA-40K	58	6015	104	B1-U5-G3
OV2-WA-LED-VPA-ASY-48LED-350mA-40K.ies	OV2-WA-LED-VPA-ASY-48LED-350mA-40K	53	5647	107	B1-U5-G3
OV2-WA-LED-VPA-SYM-36LED-350mA-40K.ies	OV2-WA-LED-VPA-SYM-36LED-350mA-40K	40	4344	109	B1-U5-G3
OV2-WA-LED-VPA-SYM-36LED-525mA-40K.ies	OV2-WA-LED-VPA-SYM-36LED-525mA-40K	58	6169	106	B2-U5-G3
OV2-WA-LED-VPA-SYM-48LED-350mA-40K.ies	OV2-WA-LED-VPA-SYM-48LED-350mA-40K	53	5792	109	B2-U5-G3
OV2-WA-LED-VPA-ASY-36LED-350mA-50K.ies	OV2-WA-LED-VPA-ASY-36LED-350mA-50K	40	4447	111	B1-U5-G3
OV2-WA-LED-VPA-ASY-36LED-525mA-50K.ies	OV2-WA-LED-VPA-ASY-36LED-525mA-50K	58	6315	109	B1-U5-G3
OV2-WA-LED-VPA-ASY-48LED-350mA-50K.ies	OV2-WA-LED-VPA-ASY-48LED-350mA-50K	53	5929	112	B1-U5-G3
OV2-WA-LED-VPA-SYM-36LED-350mA-50K.ies	OV2-WA-LED-VPA-SYM-36LED-350mA-50K	40	4561	114	B1-U5-G3
OV2-WA-LED-VPA-SYM-36LED-525mA-50K.ies	OV2-WA-LED-VPA-SYM-36LED-525mA-50K	58	6477	112	B2-U5-G3
OV2-WA-LED-VPA-SYM-48LED-350mA-50K.ies	OV2-WA-LED-VPA-SYM-48LED-350mA-50K	53	6082	115	B2-U5-G3

IES File downloads for this product can be found at www.usalgt.com/downloads/asr.html